



Integrated Mini PA/VA Unit

miniVES is scalable Public Address & Voice Alarm unit suitable for multi-purpose architectures. Devices from miniVES series are voice alarm compact control units containing all components within one compact housing, which meet all the requirements of EN 54-16 and EN 54-4 (certificate of constancy of performance 1438-CPR-0527).

Whole concept of the system is based on the high quality audio network distribution nodes equipped either with two independent 160 W or 320 W class D amplifiers, which distribute 100 V signals to 4 or 8 speaker lines depending on the type. The system also ensures operation of a backup amplifier for the Emergency priority type of signals.

miniVES is equipped with integrated backup power supply and EN 54-4 compliant charging unit. miniVES is designed to be a Plug & Play device with all elements expected from

Voice Evacuation Systems; including a built-in fire microphone, touchscreen for global control, DSP, programmable contact inputs and buttons, time scheduler, charger with battery mounting space and expandable memory size for messages – all fitted into IP30 chassis.

miniVES belongs to the family of independent EVAC systems which can be networked together and extended by desktop zone microphones or fireman microphones via TCP/IP network to provide live announcements and background music inputs. The system has been designed to be wired using CAT5 cables for paging microphones and fibre-optic redundant interlink connections between the systems.

miniVES support up to 45 high quality audio signals distributed over 254 devices in the network.

Main Features

- All in one – independent wall mount EN54-4/16 PAVA unit
- Stand alone or TCP/IP network architecture
- DSP audio processing on board
- Compatibility with RACK mounted modular MULTIVES
- Professional Sound Quality
- Evacuation, paging message and background music features
- Impedance speaker monitoring
- Simple installation
- User friendly and intuitive programming software

TECHNICAL SPECIFICATION

	miniVES 2001*	miniVES 4001*	miniVES 4002*
No of AB zones	2	4	4
No of speaker lines	4	8	8
No of control inputs	7	7	7
No of relay outputs	3	3	3
NO of amplifiers / Power	2 / 160 W RMS	2 / 320 W RMS	2 / 320 W RMS
Redundant amplifier	Yes – 160 W RMS	Yes – 320 W RMS	Yes – 320 W RMS
No of messages played at the same time	1	1	2
Protection	Over-temperature, short circuit, overload, ground leakage		
Battery working time	30 hours + 30 minutes evacuation		
Ingress protection	IP 30		
Operating condition	-5 to + 45°C / 5% to 95% humidity with no condensation		
Gross Weight	2001 – 26 kg / 4001 – 31 kg / 4002 – 31,5 kg		
Dimensions (W x H x D)	440 mm x 525 mm x 350 mm		
Finish	Black		
Optional functions			
No of audio inputs	1 – Stereo to mono		
No of audio outputs	1 – mono line output		
Network card	2x SFP module 1 Gb/s, 1x POE 1 Gb/s, 100 Mb/s, 1x LAN 1 Gb/s, 100 Mb/s connection; RS485 port; 1x LAN/WAN 100 Mb/s connection		
Basic Network card	2x Lan 1 Gb/s, 100 Mb/s, 1x LAN/WAN 100 Mb/s connection		
GUI	4,5" color touch screen		
DSP	Input EQ, outputs EQ, Feedback eliminator and audio limiter		

ABT-M01 Microphone



The ABT-M01 microphone is an affordable fully analog device. It is equipped with a built in gong generated onboard the device, accessible through the switch on the back panel.

The gong as well as the microphone itself has an individual volume control knob also placed on the back panel of the device.

To operate the device press the MIC ON button, the status LED will switch to steady green light. In the event of an active built in gong, the status LED will turn green once the gong has ended. When finished transmitting the message release the MIC ON button to deactivate the gooseneck mic.

ABT-M04 Microphone

The ABT-M04 is a 4 button analog microphone with built in gong, push to talk and bi-color LED indicating the ready-to-speak status.

To operate the device first select the Zones by pressing designated buttons and then press MIC ON button, the status LED will switch from red (not ready for broadcast) to steady green light. In the event of an active built in gong, the status LED will turn green once the gong has ended. When finished transmitting the message release the MIC ON button to deactivate the gooseneck mic.



	ABT-M01	ABT-M04
Operating voltage	20-57 VDC	
Efficiency	10 mV/a	
Output level	775 mV	
Maximum distance from amplifier	250 m	
Recommended cable type	UTP	
Connector Type	8P8C (RJ45)	
Dimensions without packaging (not more than)	150 x 60 x 165 mm	
Net weight (not more than)	1,2 kg	