



## Euro-fi Wireless Remote Indicator (Static) (EUW-RI-02)

The EUW-RI-02 Wireless Remote Indicator is a low profile unit with a large red LED panel, which can be used to indicate a variety of events or alarms on the fire system.

When used with the Euro-fi EUW-W2W-01 translator module the unit is fully programmable through the control equipment cause and effect. The device is ideal for indicating the activation of a detector which is located where visual alarm confirmation is difficult, such as a lift shaft, ceiling void or locked room. Indication of the operation of other part of the fire system is also possible.

Powered by standard lithium batteries and utilising well proven adaptive radio signal processing algorithms ensures the highest levels of life safety and reliability.

## TECHNICAL DATA

Operating frequency range	868 - 870 MHz
Max radiated power	5dBm (3mW)
Operating frequency channels	7
Communication range with translator or expander module	≤ 150m (in open space)
IP rating	42
Dimensions	80mm x 80mm x 33mm
Weight (without batteries)	120g
Primary battery	CR123A (3V & 12Ah)
Secondary battery	CR2032 (3V & 0.24Ah)
Max humidity (non condensing)	95% RH
Temperature range (non icing)	-10°C to +55°C

## KEY FEATURES

- Pleasing low profile design
- 3rd party approval to ETSI 300-220
- Bi-directional wireless communication
- 5 year product warranty
- Utilises dual low cost standard lithium batteries
- Bright indicator panel (red)
- Compatible with static Euro-fi translators and expanders
- 5 year expected battery life
- Site programmable

Note: Functionality is dependant on the control equipment.

## APPROVALS

- ETSI 300-220

## TECHNICAL INFORMATION

