



Eurotech 1 Loop Intelligent Fire Control Panel (EUR-5101N)

The Eurotech series control panels are supplied with a single loop driver card, 2 onboard sounder panels circuits, 20 programmable zonal LEDs with slide-in labels, and 25 system LEDs for information purposes. There are also 4 programmable function buttons with LED indication for confirmation of operation.

The control panel consists of the latest dual flash-based microprocessor technology combined with a high resolution, high contrast, graphical LCD display and tactile keypad providing a simple 'select & click' programming aid for engineer configuration and end user operation.

Powerful cause-and-effect programming coupled with dynamic zoning and enhanced trace diagnostics makes the panel suitable for a wide range of site applications from small to large complex multi-area systems. Fully programmable on-site via the onboard alphanumeric keypad, or PC-NeT Configuration Software.

An extensive suite of user-friendly Windows-based PC software programs has been developed to enhance your experience when using Eurotech series fire panels. The suite incorporates a number of different programmes which include configuration, service, logo and virtual panel tools to allow the flexibility of the equipment to be fully explored.

Simply adding a network card allows the panel to communicate with any other Eurotech fire panel, remote terminal, or network peripheral, such as ipGateway™, BMS or graphical interface. The network operates as a true peer-to-peer system and can be configured in a fault tolerant loop or radial format.

KEY FEATURES

- 20 programmable zonal / 25 System LEDs
- Argus Vega protocol support
- Graphical LCD user interface and support for up to 200 fire zones by default allowing full EN54 compliance without additional hardware
- Dedicated USB & RS232 Serial Port for direct PC or modem connection
- Installer friendly Auto-learn, Loop Detection and Onboard Scope facility
- Graphical display configurable for virtually any language
- Robust removable equipment chassis with plug-in connectors for simple fixing and cable termination
- Integral P-Bus for system expansion via available option cards
- Ad-NeT peer-to-peer network with up to 2000 zones
- Programmable push buttons
- Rack-mount options
- Multiple languages
- Global compliance
- Fully networkable
- 3-year warranty
- Fully programmable
- Installer's logo application

TECHNICAL SPECIFICATION

Base Technology	Dual flash-based processors with real-time clock, trace diagnostics, programmable languages and character sets
Display	White backlit 240 x 64 graphical LCD
LED Indicators	22 red (1 x Fire, 1 x More Alarms, 20 x Zonal Programmable), 1 green (Power), 13 amber and 12 bi-colour (Fault & System)
Controls	Alpha numeric keypad permitting navigation, Reset, Mute, Silence, Resound, Evacuate, and 4 x programmable push buttons
Protocol	Argus Vega
Number of Fire Zones	2000 (200 per individual panel)
Number of Loops	1
Devices per Loop	Protocol dependent
Loop Current	500mA
On-Board Sounder Circuits	2 x 1 Amp programmable
On-Board Relays	2 x 1 Amp 30v AC/DC programmable(10mA, 5v min) - expandable to 4 using MXP-507
Auxilliary Supply	1 x 24v 500mA
Programmable Input	1 x monitored programmable input on-board
Programmable Key Switch Inputs	1 x volt free input (standard enc.), 8 x inputs (M, L, D enc.)
Total Available Output Current	3A maximum available for loop current + sounder outputs + auxiliary supply
Mains Supply	200 - 240v 47-63 Hz AC (+10%, -15% tolerance) 1.0A Max
Charger Current	1A temperature compensated
Serial Port	1 x on-board RS232 connection for PC, modem, IP, or portable printer
USB Interface	1 x USB B type connection for PC communication
Programming	On-board keypad or PC running Windows tools
Event Log	5000 event & diagnostic + 500 fire
Networking	Optional plug-in network card (MXP-503 - standard, or MXP-509 - fault-tolerant)
Printer (optional)	On-board (M, L, D enclosures only)
Enclosure/Colour	Steel IP30 / RAL7035
Metalwork Options	Flushing bezel, battery box, utility enclosure, termination enclosure and rack mount

DIMENSIONS & CAPACITY

	Part Number	Dimensions	Cable Entry	Battery Capacity (internal)	
				Min	Max
		H x W x D mm	(20mm knockouts)		
Standard	EUR-5101N	345 x 345 x 85	13 x top, 8 x rear	24v 4Ah	24v 7Ah
Medium	EUR-5101NM	345 x 430 x 120	13 x top, 11 x rear	24v 4Ah	24v 12Ah
Large	EUR-5101NL	475 x 450 x 120	13 x top, 11 x rear	24v 4Ah	24v 18Ah
Large - Deep	EUR-5101ND	475 x 450 x 190	13 x top, 11 x rear & 3 bottom	24v 4Ah	24v 45Ah